

RCP P/N : RC-66Q  
Radio : Various LMR radio/batteries

## Features

- Auto detect battery chemistry
- Multi-chemistry charger for Ni/Cd, NiMH, Li-ion, LiPoly batteries
- RoHS compliant
- Safe, efficient charging.
- Battery wake-up, Over Charge, Temperature, short circuit, Time out protection
- LED operator display State of Charge

## Electrical Specifications

Multi chemistry: Li-Ion, Li-Poly, Ni/MH and Ni/Cd  
Charging Rate: <1 Amp per bay  
Input: 110-132 VAC at 50/60 Hz  
200-265VAC ay 50/60 Hz  
10.8-30VDC

## Environmental Characteristics

Operating temperature: Li chemistry 0°C~45°C  
Ni chemistry 0°C~45°C  
Storage temperature: -20°C~70°C @ 85-95% Rh

## Charger Dimensions

Length: 20.0 inch (508mm)  
Width: 7.0 inch (117.8mm)  
Height: 4.5 inch (114mm)  
Weight: 5.5.Lbs

## RC-66Q Series Charger

Replaces RCP PN RPSCAU6-CHR

## RC-66Q Charger Advantages

The Richcom Power 6 Bank Charging System is an affordable, straight line design that enables the user to configure and charge multiple LMR radio batteries within the same system.



## Richcom Power Quality Promise

Richcom warranties the charger and adapters to be free of defects related to materials and workmanship for 24 months.

## About Richcom Power

Richcom Power LLC ("RCP") is headquartered in the USA with manufacturing facilities in USA, Taiwan and Shenzhen. We service an international client base using state of the art production techniques and are ISO 9001 certified.

Richcom Power commitment is to customer satisfaction. We believe our expertise and our company culture are key elements to our quality story.

Richcom Power has over 40 years experience in design, development and manufacturing rechargeable batteries and chargers for the mobile power industry.

## Richcom Power LLC

1 Tara Boulevard, Suite 200, Nashua NH 03062, USA  
+1-603-324-7152 ■ sales@richcompower.com

**RCP P/N : RC-6XQ**
**Adapter Cup Legend**

<b>Radio Model</b>	<b>Adapter PN</b>	<b>Radio Model</b>	<b>Adapter PN</b>
Harris P7300 series	NPA9	Motorola	CP150
Harris P7100 series	P71X	Motorola	CP40
Kenwood	KNB14	Motorola	CP2000
Kenwood	KNB15	Motorola	EP450
Kenwood	KNB16	Motorola	PR400
Kenwood	KNB17	Motorola	GP3688
Kenwood	KNB20	Motorola	GP300
Kenwood	KNB22	Motorola	P110
Kenwood	KNB24	Motorola	GP350
Kenwood	KNB25	Motorola	P1225
Kenwood	KNB26	Motorola	GP88
Kenwood	KNB35L	Motorola	HT1000
Kenwood	PB43	Motorola	MTS2000
Icom	BP209	Motorola	GP900
Icom	BP210	Motorola	GP1200
Icom	BP231	Motorola	MTX8000
Icom	BP232	Motorola	MTX9000
Motorola	XTS3000	Motorola	Pro5150
Motorola	XTS3500	Motorola	Pro7150
Motorola	XTS5000	Motorola	Pro9150
Motorola	APX	Motorola	GP340
Motorola	HT750	Motorola	GP380
Motorola	HT1250	Motorola	GP328 plus
Motorola	HT1550	Uniden	APX1105
Motorola	GP328	Uniden	APX1115

Contact your local Richcom Power representative or check the complete listing at [www.Richcompower.com](http://www.Richcompower.com)

**Richcom Power LLC**

1 Tara Boulevard, Suite 200, Nashua NH 03062, USA  
+1-603-324-7152 ■ [sales@richcompower.com](mailto:sales@richcompower.com)


[www.RichcomPower.com](http://www.RichcomPower.com)